



Fan Filter- ENF1500, Exit Filter- ENFI1500

Enza Fan Filter are widely used in control panels, junction boxes, power distribution box, automation equipment, electronic & power device etc.



Technical Datasheet

Model	ENF1500
Available Colors	RAL 7032 & RAL 7035
Fan Size	148 x 148 mm
Enclosure Cut-out	125 x 125 mm
Airflow Rate	66 m ³ /h (138 m ³ /h) – (Air Flow Direction “out”)
Rated Current (A)	0.08/ 0.07
Power Consumption (W)	16
Axial Fan	Ball Bearing & Body Aluminum alloy die casting material
Noise Level (dB)	39/42
Connection	2 Stranded wires, 300mm or 3-pole clamp for 2.5mm ² , clamping torque 0.8Nm max
Mounting Frame	Can fix by fast fixing clip or fix by screws
Filter material	New ABS material confirms to RoHS
Operating/ Storage Temperature	-25 to +65 °C
Operating / Storage humidity	Max 90% RH (non-condensing)
Protection Type	IP54